

CHR004

2/6/12V 600mA Lead Acid Battery Charger

Item ref: 690.004UK

User Manual

Function:

This charger is designed for use with 2V, 6V or 12V lead acid batteries only. There is a built-in poly-switch for over current protection and polarity reverse protection to ensure that the battery won't be damaged during the charging process. The appropriate battery voltage can be selected via the switch on the front of the unit and a set of crocodile clips attached to a fixed 1.2m fly lead enable easy attachment to your battery.

Technical data:

Input Voltage: 100-240V 60/50Hz 10W (max)

Output Voltage:
Charging current:
Output power:
Battery capacity:

DC 2/6/12V
600mA
7.2VA (max)
12Ah (max)

Instruction:

- 1. Read the instructions in full before attempting to charge your battery.
- 2. Insert the charger into the AC outlet and the green CHARGE LED lights up.
- 3. Select the appropriate battery voltage 2V/6V/12V through the voltage selector on the unit.
- 4. Connect the crocodile clips to the appropriate terminals on the battery and the charging process commences.
- 5. The red POL LED will light up if you have connected the terminals incorrectly.
- 6. Disconnect the charger from the AC outlet when the battery is full and the green CHARGE LED goes out.
- 7. Disconnect the charger from the battery.
- 8. The recommended charge current for lead acid batteries is around 10% of battery capacity.

Warning:

- 1. For indoor use **ONLY**.
- 2. Do not charge non-rechargeable batteries.
- 3. Use this charger with 2/6/12V lead acid batteries only.
- 4. During the charging process, the battery must be placed in a well-ventilated area.
- 5. This appliance is not intended for use by persons (including young children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for their safety.
- 6. Please dispose of any battery safely once you have finished with it.
- 7. Young children should be supervised to ensure they do not play with the appliance.

Errors and omissions excepted. Copyright© 2016. AVSL Group Ltd.